


### ERL



ERL  
旋轉二通




### 公制 Metric-BSPT(R)

型號 Model	ΦD	R	L1	L2	L3	ΦP	圖號
ERL4-M5	4	M5	3.5	18.5	29	11	12
ERL4-M6		M6	4	18.5	29.5	11	12
ERL4-01		R 1/8	8	18.5	33.5	11	14
ERL6-M5	6	M5	3.5	19.5	30	13	12
ERL6-M6		M6	4	19.5	30.5	13	12
ERL6-01		R 1/8	8	19.5	34.5	13	14
ERL6-02	R 1/4	11	19.5	35.5	13	17	
ERL8-01	8	R 1/8	8	23	38	14.5	14
ERL8-02		R 1/4	11	23	38	14.5	17
ERL8-03		R 3/8	12.5	23	41	14.5	21
ERL8-04		R 1/2	15	23	43.5	14.5	24
ERL10-02	10	R 1/4	11	27.5	41.5	18.5	17
ERL10-03		R 3/8	12.5	27.5	43.5	18.5	21
ERL10-04		R 1/2	15	27.5	45.5	18.5	24
ERL12-03	12	R 3/8	12.5	29.5	44	21	21
ERL12-04		R 1/2	15	29.5	46	21	24
ERL16-04	16	R 1/2	15	32.5	54	26	27
ERL1/4-01	1/4	R 1/8	8	19.5	34.5	13	14
ERL1/4-02		R 1/4	11	19.5	35.5	13	17
ERL5/16-01	5/16	R 1/8	8	23	38	14.5	14
ERL5/16-02		R 1/4	11	23	38	14.5	17
ERL5/16-03		R 3/8	12.5	23	41	14.5	21
ERL5/16-04		R 1/2	15	23	43.5	14.5	24
ERL3/8-02	3/8	R 1/4	11	27.5	41.5	18.5	17
ERL3/8-03		R 3/8	12.5	27.5	43.5	18.5	21
ERL3/8-04		R 1/2	15	27.5	45.5	18.5	24
ERL1/2-03		1/2	R 3/8	12.5	29.5	44	21
ERL1/2-04	R 1/2		15	29.5	46	21	24

### ESPC



ESPC  
截止閥直通



### 公制 Metric-BSPT(R)

型號 Model	ΦD	R	L1	L2	L3	ΦP	圖號
ESPC4-M5	4	M5	3.5	31.5	15	10	10
ESPC4-01		R 1/8	7.5	24.5			10
ESPC4-02		R 1/4	10	24.5			14
ESPC6-M5	6	M5	3.5	35	16	12	12
ESPC6-01		R 1/8	7.5	27.5			12
ESPC6-02		R 1/4	10	27.5			14
ESPC8-01	8	R 1/8	7.5	31.5	18.5	14	14
ESPC8-02		R 1/4	10	33.5			14
ESPC8-03		R 3/8	10.5	33.5			17
ESPC8-04		R 1/2	13.5	33.5			21
ESPC10-01	10	R 1/8	7.5	34	20	17	17
ESPC10-02		R 1/4	10	35			17
ESPC10-03		R 3/8	10.5	35			17
ESPC10-04		R 1/2	13.5	35			21
ESPC12-03	12	R 3/8	10.5	36.5	23	20.5	21
ESPC12-04		R 1/2	13.5	36.5			21